

FLOE 24 VOLT SOLAR PANEL FOR 6000-7500# VSD BOAT LIFTS WITHOUT A CANOPY Blue quick connect 3. Run the solar panel wire down the corner post (on the drive train corner) and to the To drive train battery tray. Cut the 1/2" Velcro to lengths needed to secure the wire to the insert. Gray quick connect Coil any excess wire and secure to frame with Velcro. Place the battery in the battery box and set on the battery tray. See Fig. 3. Red tape 12 Volt Battery # 1 12 Volt Battery # 2 Battery box cover Black Smooth wire Grooved wire Battery box Battery box Solar panel wire Solar panel Velcro 12 Volt battery Battery tray Fig. 4 4. Connect the solar panel to the battery as shown in Fig. 4. The smooth wire with red tape connects to the positive post on the first battery and the grooved wire connects to the negative post on the second battery. Strap the battery box cover to the battery box.

Instruction P/N 611-01325-00 Issue: 2/27/04

Fig. 3

Drive train box

Sheet 2 of 2